

Bogotá D.C., 16 de mayo de 2024

Señores
CONSEJO SUPERIOR DE LA JUDICATURA
Atn. Adalberto Coronell
Supervisor

Ref.: Solicitud Cambio de procesador Orden de compra No. 128202

Respetados Señores:


Teniendo en cuenta la adjudicación correspondiente al LOTE 6 a favor de Nexcom SAS, y de acuerdo al RFI de la entidad, donde el procesador inicial ofertado fue ACER RYZEN AMD 5 7535U , con el cual fuimos adjudicados; esto teniendo en cuenta que el fabricante de la marca ACER, nos manifiesta sobre la dificultad en la producción de máquinas en la plataforma AMD, nos permitimos ofrecer a la entidad para este LOTE 6 un nuevo modelo de procesador ACER Travel Mate P214 - Intel CORE I5-1335U el cual cumple con todas las condiciones técnicas y rendimiento.

Adjuntamos al presente comunicado, la ficha técnica del procesador a entregar dando cumplimiento a lo requerido técnicamente por la entidad en el RFI.

Se aclara la entidad, que el cambio solicitado es solamente para el procesador de la maquinas, las demás condiciones técnicas continúan igual.

Agradezco la atención a la presente, quedando atentos a su pronta respuesta,

Cordialmente,


Uriel Roman Camargo
Representante Legal Nexcom SAS



TravelMate P214-55 Specifications (v8-0-7)			
Category		Description	Footnotes
Operating system	1	Windows 11 Pro (Acer recommends Windows 11 Pro for business.) Windows 11 Home	
CPU and chipset	1	<p>Intel® Core™ i7-1365U processor (12 MB Smart Cache, 1.8 GHz Performance-core with Intel® Turbo Boost Technology 2.0 up to 5.2 GHz, Intel® vPro™ Eligibility), supporting hybrid core architecture with Performance-core and Efficient-core</p> <p>Intel® Core™ i7-1355U processor (12 MB Smart Cache, 1.7 GHz Performance-core with Intel® Turbo Boost Technology 2.0 up to 5.0 GHz), supporting hybrid core architecture with Performance-core and Efficient-core</p> <p>Intel® Core™ i5-1345U processor (12 MB Smart Cache, 1.6 GHz Performance-core with Intel® Turbo Boost Technology 2.0 up to 4.7 GHz, Intel® vPro™ Eligibility), supporting hybrid core architecture with Performance-core and Efficient-core</p> <p>Intel® Core™ i5-1335U processor (12 MB Smart Cache, 1.3 GHz Performance-core with Intel® Turbo Boost Technology 2.0 up to 4.6 GHz), supporting hybrid core architecture with Performance-core and Efficient-core</p> <p>Intel® Core™ i3-1315U processor (10 MB Smart Cache, 1.2 GHz Performance-core with Intel® Turbo Boost Technology 2.0 up to 4.5 GHz), supporting hybrid core architecture with Performance-core and Efficient-core</p>	
Memory	1, 2, 3	<p>Dual-channel DDR4 SDRAM support:</p> <ul style="list-style-type: none"> Up to 16 GB of DDR4 system memory, upgradable to 32 GB using two soDIMM modules <p>Memory Frequency : Up to 3200 MT/s</p>	3, 4
Display		<p>14.0" display with IPS (In-Plane Switching) technology, WUXGA 1920 x 1200, Acer ComfyView™ LED-backlit TFT LCD</p> <p>16:10 aspect ratio, color gamut NTSC 45%</p> <p>Wide viewing angle up to 170 degrees</p> <p>Mercury free, environment friendly</p>	5
Graphics		<p>Intel® Iris® X^e Graphics eligible</p> <p>Graphics Special Technology:</p> <ul style="list-style-type: none"> AVC/H.264, HEVC/H.265, VP8, VP9, AV1, MPEG-2, JPEG HW Accelerated Video Decode AVC/H.264, HEVC/H.265, VP9, MPEG-2, JPEG HW Accelerated Video Encode 	6

TravelMate P216-51 Specifications (v8-0-7)			
		<ul style="list-style-type: none"> • OpenGL ES 3.2 • WebGL & HTML5 • Vulkan <p>Intel® UHD Graphics</p> <p>Graphics Special Technology#</p> <ul style="list-style-type: none"> • AVC/H.264, HEVC/H.265, VP8, VP9, AV1, MPEG-2, JPEG HW Accelerated Video Decode • AVC/H.264, HEVC/H.265, VP9, MPEG-2, JPEG HW Accelerated Video Encode • OpenGL ES 3.2 • WebGL & HTML5 • Vulkan 	6
Audio		<ul style="list-style-type: none"> • DTS® Audio, featuring optimized bass response and micro-speaker distortion prevention • Acer Purified.Voice technology with AI noise reduction in dual built-in microphones. Features include far-field pickup, dynamic noise reduction through neural network, adaptive beam forming, and pre-defined personal and conference call modes. • Acer TrueHarmony technology for lower distortion, wider frequency range, headphone-like audio and powerful sound 	
Storage		<p>Solid state drive</p> <ul style="list-style-type: none"> • SSD slot: 2 • 256 GB / 512 GB / 1 TB, PCIe Gen4, 16 Gb/s, NVMe <p>Hard disk drive</p> <ul style="list-style-type: none"> • Optional 2nd HDD 1 TB, 2.5-inch 5400 RPM <p>(Notes: LTE SKU not support HDD option)</p>	1, 7 1, 7
Webcam	1	<p>Video conferencing</p> <p>UFC with</p> <ul style="list-style-type: none"> • T-Type USB FHD camera + IR camera • Compatible with Windows • 1920 x 1080 resolution • 1080p HD video at 60 fps with Temporal Noise Reduction • Dual Mic (33 mm + 33 mm) • 78 x 3.2 (5.2) x 3 mm <p>UFC with</p> <ul style="list-style-type: none"> • T-Type HD camera • Compatible with Windows only • 1280 x 720 resolution • 720p HD video at 30 fps with Temporal Noise Reduction • Blue Glass lens • Dual Mic (33 mm + 33 mm) • 78 x 3.2 (5.2) x 3 mm 	
Wireless and networking	1	<p>WLAN</p> <ul style="list-style-type: none"> • Intel® Wireless Wi-Fi 6E AX211 	

TravelMate P216-51 Specifications (v8-0-7)		
		<ul style="list-style-type: none"> • 802.11 a/b/g/n/ac/ax wireless LAN • Band: 2.4 GHz, 5 GHz and 6 GHz • 2x2 MU-MIMO technology • Support Bluetooth® 5.1 or above • Support vPro • Intel® Wireless Wi-Fi 6E AX211 • 802.11 a/b/g/n/ac/ax wireless LAN • Band: 2.4 GHz, 5 GHz, and 6 GHz • 2x2 MU-MIMO technology • Support Bluetooth® 5.1 or above • Support CNVi interface <p>WWAN</p> <ul style="list-style-type: none"> • LTE FDD: B1/B2/B3/B4/B5/B7/B8/B12/B13/B14/B17/B18/B19/B20/B25/B26/B28/B29/B30/B32/B66/B71 • LTE TDD: B34/B38/B39/B40/B41/B42/B43/B46/B48 • WCDMA/HSPA+: B1/B2/B3/B4/B5/B6/B8/B19 • Support up to LTE Cat.6 • LTE Data Rate: Maximum download 300 Mbps, upload 50 Mbps • WCDMA Data Rate: Maximum download 384 kbps, upload 385 kbps • DC-HSPA+: Maximum download 42 Mbps • eSIM is included <p>LAN</p> <ul style="list-style-type: none"> • Gigabit Ethernet
Security		<p>Acer ProShield Plus security manager includes:</p> <ul style="list-style-type: none"> • Data Protection: File & Folder Encryption and Decryption, Personal Security Drive • Data Removal: File Shredding • Security Alert: Invalid Access Alert, Security Report <p>Acer Bio-Protection fingerprint solution, featuring computer protection and Windows Hello Certification</p> <p>Discrete Trusted Platform Module (TPM) solution</p> <p>BIOS user, supervisor, SSD passwords</p> <p>Kensington lock slot</p>
Dimensions and weight	1, 8, 9	<p>Dimensions</p> <ul style="list-style-type: none"> • 358.5 (W) x 260 (D) x 19.9/22.9 (H) mm (14.11 x 10.24 x 0.78/0.9 inches) with Plastic A Cover <p>Weight</p> <ul style="list-style-type: none"> • 1.87 kg (4.12 lbs.) with 3-cell battery pack, one SSD
Power adapter and battery	1	<p>Battery</p> <ul style="list-style-type: none"> • 65 Wh 3-cell Li-ion battery • Supports Fast Charging technology (for models with Full HD Panel + SSD) <p>Battery life:</p> <p>Up to 13 hours (based on MobileMark® 2018 test results)</p>

TravelMate P216-51 Specifications (v8-0-7)		
		<p>HDMI[®] 2.1 port with HDCP support</p> <p>USB Type-C</p> <p>USB Type-C[™] port supporting:</p> <ul style="list-style-type: none"> • USB4[®] 40Gbps • DisplayPort over USB-C • Thunderbolt[™] 4 • USB charging 5 V; 3 A • DC-in port 20 V; 65 W
Windows Desktop Apps	11	<p>In-House</p> <ul style="list-style-type: none"> • Acer Control Center • Acer Product Registration • Quick Access
Options and accessories		<p>Accessory</p> <p>SIM Card Tray Ejector Pin</p> <p>Support Add-on features for Acer Type-C Dock III (ADK930)</p> <ul style="list-style-type: none"> · MAC address pass-through to Dock (for host MAC address) · Wake-on-LAN from Sleep mode · PXE boot via Dock LAN port <p>Support Acer USB Type-C Dock III (ADK930)</p> <ul style="list-style-type: none"> · Dimension: 190 (W) x 85.3 (D) x 26.7 (H) mm (7.48 x 3.36 x 1.05 inches) · Weight: 233 g (0.52 lbs) · Supporting up to three video port (two DP 1.2, one HDMI 2.0), external display number by condition · One USB Type-C upstream port to host · One USB Type-C downstream port for device (data only) · Three USB 3.1 (one BC1.2) ports · Ethernet (RJ45) port · Up to 85 W power supply delivering to system · Audio Combo Jack · 1 m USB Type-C cable · Vertical mode with stand · VESA mount mode <p>Support Add-on features for Acer Type-C Dock II (ADK810)</p> <ul style="list-style-type: none"> · MAC address pass-through to Dock (for laptop with LAN chip) · Power button mirrors the host's · Wake-on-LAN from Sleep/Hibernate/Off mode · PXE boot via Dock LAN port · LED behavior aligned with the host power status <p>Support Acer USB Type-C Dock II (ADK810)</p> <ul style="list-style-type: none"> · Dimension: 204 (W) x 87 (D) x 23.9 (H) mm (8.03 x 3.42 x 0.94 inches) · Weight: 250 g (0.55 lbs) · Supporting up to three displays (one DP 1.2, two HDMI 2.0) with OS driver installed · One USB Type-C upstream port to host

TravelMate P216-51 Specifications (v8-0-7)		
	<ul style="list-style-type: none"> · One USB Type-C downstream port for device (data only) · Three USB 3.1 (one BC1.2) ports · Ethernet (RJ45) port · Up to 60 W power supply delivering to system · Audio Combo Jack · 1 m USB Type-C cable · Vertical mode with stand · VESA mount mode 	
System compliance	ENERGY STAR® Wi-Fi® EPEAT® Gold	
Warranty	One-year International Travelers Warranty (ITW)	
Quality and reliability tests	Temperature and humidity Hinge life Weight and pressure Acoustics Spillage Free drop Shock and vibration Electrostatic discharge immunity Keyboard-switch life MTBF (mean time between failures) Military Reliability Test: Mechanical Shock, Transit Drop (Packaged) 122 cm (MIL-STD 810H) Military Reliability Test: Mechanical Shock, Transit Drop (Unpackaged) 122 cm (MIL-STD 810H) Military Reliability Test: Vibration (MIL-STD 810H) Military Reliability Test: Sand and Dust (MIL-STD 810F) Military Reliability Test: Humidity (MIL-STD 810H) Military Reliability Test: Rain (MIL-STD 810H) Military Reliability Test: Low Temperature (MIL-STD 810H) Military Reliability Test: High Temperature (MIL-STD 810H)	12
Others	<ul style="list-style-type: none"> • Reset hole • Power LED indicator 	
<ol style="list-style-type: none"> 1. Specifications vary depending on model. 2. Shared system memory may be allocated to support graphics, depending on system memory size and other factors. Actual system memory available to the operating system will be reduced by any memory used by the graphics solution and resources required by the operating environment. 3. Memory speed may vary, depending on the CPU, chipset or memory fitted. 4. A 64-bit operating system is required to enjoy the ultimate performance of 4 GB or higher memory. 5. All brands and product names mentioned herein include trademarks of their respective companies and are used solely to describe or identify the products. 6. Not all features indicated are supported on all SKUs 		

TravelMate P216-51 Specifications (v8-0-7)

7. 1 GB is 1 billion bytes. Actual formatted capacity is less and may vary depending on preloaded materials and operating environment. Acer Recovery Management uses a portion of the stated hard disk capacity as dedicated backup space.
8. Minor variations in system dimensions are possible due to the manufacturing process.
9. Weight may vary depending on product configuration, vendor components, manufacturing variability, and selected options.
10. *Actual battery life may vary considerably by specifications, depending on product model, configuration, applications, power management settings, operating conditions, and features utilized. Performance variation also arises based on components in use, which includes but is not limited to the processor, RAM capacity, storage, display and resolution, etc.*
11. Bundled software may vary depending on hardware configuration, OS and regional availability.
12. *MIL-STD 810G/H is a testing protocol conducted in controlled settings and does not guarantee future performance in all situations. Do not attempt to simulate these tests, as damage resulting from this will not be covered by Acer's standard warranty.*

In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.

© 2023. All rights reserved.

Microsoft and Windows are registered trademarks of Microsoft Corporation.

Ultrabook, Celeron, Celeron Inside, Core Inside, Intel, Intel Logo, Intel Arc graphics, Intel Atom, Intel Atom Inside, Intel Core, Intel Inside, Intel Inside Logo, Intel vPro, Intel Evo, Pentium, Pentium Inside, vPro Inside, Xeon, Xeon Inside, Intel Agilex, Arria, Cyclone, Movidius, eASIC, Ethernet, Iris, Killer, MAX, Select Solutions, Si Photonics, Stratix, Tofino, and Intel Optane are trademarks of Intel Corporation or its subsidiaries.

About Acer

Founded in 1976, Acer is one of the world's top ICT companies with a presence in more than 160 countries. As Acer evolves with the industry and changing lifestyles, it is focused on enabling a world where hardware, software and services will fuse with one another, creating ecosystems and opening up new possibilities for consumers and businesses alike. Acer's 7,500 employees are dedicated to the research, design, marketing, sale, and support of products and solutions that break barriers between people and technology. Please visit www.acer.com for more information.



TravelMate P216-51 Specifications (v8-0-7)



Purified.Voice



PurifiedVoice with
AI Noise Reduction



Data Access



TPM



OceanGlass™
Touchpad



Appendix

v5-0-5 (Ver. 2)

About

Wireless and networking

Software

Input and control

Quality and reliability tests

Graphics

Dimensions and weight

v6-0-6 (Ver. 3)

Webcam

Security

Power adapter and battery

Input and output

Storage (Notes Changed)

v7-0-7 (Ver. 4)

Power adapter and battery

Options and accessories

v8-0-7 (Ver. 5)

Quality and reliability tests